

[Quick Start Guide]



QUICK START GUIDE

SilverStorm™ 9040 INSTALLATION



Purchasers of OEM products should consult with the OEM for support.

Support Headquarters

QLogic Corporation
4601 Dean Lakes Blvd
Shakopee, MN 55379

QLogic Web Site

www.qlogic.com

Technical Support Web Site

support.qlogic.com

Technical Support Email

support@qlogic.com

Technical Training Email

tech.training@qlogic.com

North American Region

Email

support@qlogic.com

Phone

+1 952-932-4040

Fax

+1 952-932-4018

All other regions of the world

QLogic Web Site

www.qlogic.com

SilverStorm 9040

Quick Start Guide

Pre-Installation Checklist

Before beginning the actual installation, the Site Implementation Engineer must perform the following tasks:

Step 1. Check the packing list to verify all ordered equipment has been received. The box should contain:

- ☐ A SilverStorm 9040 switch with the following pre-installed:
 - ☐ Two (2) fan units
 - ☐ Power supplies and blanks (4 total).
 - ☐ InfiniBand (IB) leaf modules (up to 4 total)
 - ☐ Virtual I/O hardware such as the SilverStorm™ FibreChannel Virtual I/O Card (FVIC) and the SilverStorm™ Ethernet Virtual I/O Card (EVIC) (up to 4 total)
 - ☐ Any leaf/VIO hardware blanks (up to 3 total).
 - ☐ Spine module
- ☐ Additional parts:
 - ☐ One (1) Hardware installation kit (mounting rails, etc.)
 - ☐ One (1) Serial cable DB-9 female to RJ-11 connectors
 - ☐ One (1) Cat6 RJ-11 Serial cable
 - ☐ Power cords (up to 2 total)
 - NOTE:** Be certain that the power cords are firmly seated into the SilverStorm 9040 power supplies AC power inlets.
- ☐ A CD ROM containing:
 - ☐ Technical Documentation
 - ☐ Software
 - ☐ Release Notes.

Step 2. Unpack the equipment.

Step 3. Inspect the equipment for any shipping damage.

NOTE: Any shipping damage should be reported to the shipping company.

Step 4. Verify that the equipment shipped matches the packing list.

Tools and Equipment Required

- ☐ An ESD wrist strap
- ☐ A #2 Phillips screwdriver
- ☐ Pen (felt-tip) to mark the mounting holes on the rack

Installation Tasks

To perform the actual switch installation, the site implementation engineer must perform the following tasks, which are detailed in this section.

Step 1. Check the installation site to verify the installation of cabinet power feeds, rails, and grounding.

Step 2. Inspect the packaging and equipment for any shipping damage. Any shipping damage should be reported to the shipping company. Only unpack the the equipment if there is no shipping damage.

Step 3. Record the equipment serial numbers.

Step 4. Physically install the switch in the rack.

Step 5. Install InfiniBand (IB) or IB/Fiber Optic cables between the SilverStorm 9040 and network devices.

Step 6. Install intra-cabinet power and grounding cables for the switch.

Step 7. Power up the switch.

Step 8. Change the default system IP address (192.168.100.9) and gateway IP address (255.255.255.0).

Step 9. Add the equipment to the network.

Changing the IP Address and Default Gateway

Using the RS232 Serial Port

Step 1. Connect null-modem/crossover serial cables to the RS-232 port of the switch spine module. If using a terminal emulation device, the settings should be:

- ☐ 8 data bits
- ☐ no parity bits
- ☐ 1 stop bit
- ☐ 56K baud
- ☐ Use VT100 emulation.
- ☐ Flow control = XON/XOFF

Step 2. Power up the switch.

Step 3. To change the switch default IP address enter:

```
setChassisIpAddr -h ipaddress -m netMask
```

where **-h ipaddress** is the new IP address in dotted decimal (i.e., xxx.xxx.xxx.xxx) format, and **-m netMask** is the new subnet mask in dotted decimal (i.e., xxx.xxx.xxx.xxx) format.

Step 4. To change the switch default gateway IP address enter:

```
setDefaultRoute -h ipaddress
```

where **-h ipaddress** is the new default gateway IP address in dotted decimal (i.e., xxx.xxx.xxx.xxx) format.

Using Telnet or SSH

Step 1. Power up the switch.

Step 2. Connect a Category 5 or 6 (Cat 5/6) Ethernet cable to the RJ-45 connector on the switch. Connect the other end of the Cat 5/6 to a OOB LAN workstation.

Step 3. Access the switch with the following command:

```
telnet 192.168.100.9
```

Step 4. The system prompts for a user name. In order to change the IP address and default gateway, the user must be logged in as the administrator. At the prompt enter:

```
admin
```

Step 5. The system prompts for a password. At the prompt enter:

```
adminpass
```

The system responds with:

```
Welcome to the SilverStorm 9040 CLI. Type 'list' for the list of commands.
```

Step 6. To change the switch default IP address enter:

```
setChassisIpAddr -h ipaddress -m netMask
```

where **-h ipaddress** is the new IP address in dotted decimal (i.e., xxx.xxx.xxx.xxx) format, and **-m netMask** is the new subnet mask in dotted decimal (i.e., xxx.xxx.xxx.xxx) format.

Step 7. To change the switch default gateway IP address enter:

```
setDefaultRoute -h ipaddress
```

where **-h ipaddress** is the new default gateway IP address in dotted decimal (i.e., xxx.xxx.xxx.xxx) format.

Step 8. To to exit the CLI enter:

```
logout
```

Using the Chassis Viewer

Step 1. Power up the switch.


Step 2. Connect a Category 5 or 6 (Cat 5/6) Ethernet cable to the RJ-45 connector on the switch. Connect the other end of the Cat 5/6 to a OOB LAN workstation.

Step 3. To start Chassis Viewer, open a web browser and enter the IP of the switch.

NOTE: The browser must be on a workstation connected to the same Ethernet LAN, and on the same TCP/IP subnet as the switch RJ-45 OOB LAN port.

Step 4. From the main menu select OOB LAN IP then Set OOB LAN IP. The following screen is displayed:

Figure 1. Set OOB LAN IP Window



The image shows a window titled "Set OOB LAN IP" with a question mark icon in the top right corner. It contains two input fields: "Out of Band LAN IP" with the value "172.26.100.236" and "Net Mask" with the value "255.255.255.0". At the bottom, there are three buttons: "Apply", "Refresh", and "Close".

Set OOB LAN IP	
Out of Band LAN IP	172.26.100.236
Net Mask	255.255.255.0
<div>Apply Refresh Close</div>	


Step 5. Type in the new switch IP address.

Step 6. Type in the new net mask.

Step 7. Click Apply.

Step 8. To change the switch default gateway, from the main menu select OOB LAN IP then Set Default Gateway IP. The following screen is displayed:

Figure 2. Set Default Gateway IP Window



The image shows a window titled "Set Default Gateway IP" with a question mark icon in the top right corner. It contains one input field: "Gateway address" with the value "172.26.100.100". At the bottom, there are three buttons: "Apply", "Refresh", and "Close".

Set Default Gateway IP	
Gateway address	172.26.100.100
<div>Apply Refresh Close</div>	

Step 9. Type in the correct switch default gateway IP address.

Step 10. Click Apply.

NOTE: A reboot is required to activate the new gateway IP address.

Activating/Deactivating the Embedded Fabric Manager

If the embedded (FM) has been purchased, it requires a license key to activate it via Chassis Viewer. The license key information is contained in an envelope marked "Fabric Manager License". This envelope is packed in the box with the switch. For detailed information on activating the Fabric Manager, refer to the "License Keys; Key Administration" and "QuickSilver Fabric Manager Control" sections of the *SilverStorm 9000 Users Guide*.

Installing Documentation from a CD

Installing Documentation on a Linux Host

Step 1. Place the Documentation CD in the CD-ROM drive.

Step 2. Check that the CD has been mounted. Type `ls /mnt/cdrom`. The system returns a list of files on the CD.

Step 3. Create a subdirectory on the drive where the documentation will reside.

Step 4. Type `cp /mnt/cdrom/<SUBDIRECTORY NAME> /<SUBDIRECTORY NAME>` to copy the documentation to the subdirectory created in Step 3.

Step 5. Navigate to the Documentation directory and open the desired PDF file.

Declaration of Conformity

QLogic Corporation.
26650 Aliso Viejo Parkway
Aliso Viejo, CA 92656
Phone: 949.389.6000
www.qlogic.com

QLogic Corporation declares the following product is in compliance with the following standards.

Product identification:

Name: 48 Port InfiniBand Switch
Model/Type: SilverStorm 9040

Standards applied:

FCC Part 15, Subpart B, Class A; ICES-003; EMC; EN55022, Class A, EN61000-3-2 and EN61000-3-3; VCCI, Class A and EN55024

Test House:

Test report is issued by:
Name: Underwriters Laboratories Inc.
Address: 1285 Walt Whitman Road, Melville, NY 11747-3081 USA
Test dates: 2004-10-27 to 11-05
File No: E231432
Project No: 04ME12243



Vladimir Tamarkin
Director, Mechanical Engineering

© 2007 QLogic Corporation. QLogic, the QLogic logo, the Powered by QLogic logo, SANbox, SANsurfer, and SANsurfer Management Suite are registered trademarks or trademarks of QLogic Corporation. All other brands and product names are trademarks or registered trademarks of their respective owners. Information supplied by QLogic is believed to be accurate and reliable. QLogic Corporation assumes no responsibility for any errors in this brochure. QLogic Corporation reserves the right, without notice, to make changes in product design or specifications.



QLogic Corporation
949.389.6000

26650 Aliso Viejo Parkway
www.qlogic.com

Aliso Viejo, CA 92656

D000010-004 Rev. A